

## **FIELD OF THE INVENTION**

## **BACKGROUND OF THE INVENTION**

Figures 1 illustrates prior art digital decoder 100 for a NTSC/PAL television receiver. Digital decoder 100 operates on composite video signals that conform to NTSC/PAL standards in three main stages. Specifically, after analog-to-digital (hereinafter A/D) converter 102 generates digitized composite signal 104 based on the incoming signals, Y/C separator 106 separates out luminance (Y) and chrominance (C) from this digitized composite signal 104. Because display

3

e

Y/C separator 200 however has trouble with diagonal lines and vertical color changes. With diagonal lines, Y/C separator 200's C signal as shown in Figure 2(a) includes the difference between adjacent luminance values, which may be interpreted as chrominance information. Such interpretation results in cross-color artifacts. As for vertical color transitions, the so-called "dot crawl" artifact surfaces due to imperfect removal of color information from Y/C separator 200's Y signal as shown in Figure 2(a).

Y/C separator 220 as illustrated in Figure 2(b) is an improved solution over Y/C separator 200. Particularly, Y/C separator 220 includes vertical correlation detector 222, which determines the amount of line-to-line correlation. If line 1 (hereinafter L1) and line 2 (hereinafter L2) are highly correlated, vertical correlation detector 222 causes multiplexer (hereinafter Mux) 224 to select L2-L1 as its output. If L2 and line 3 (hereinafter L3) are highly correlated, the output of Mux 224 is then L2-L3. Although Y/C separator 220 may address the aforementioned cross-color and dot crawl artifacts, it may have problems with real-world video. More specifically, it may not have sufficiently correlated lines to adequately separate the luminance and chrominance signals as occurs with high resolution cameras and computer graphics animation. So, the more detail that is present in digitized composite video 104, the greater the artifacts would be introduced by Y/C separator 220.

09745248 " 122000

As for many of the existing PAL televisions, they utilize Y/C separators that are similar to their NTSC counterparts as shown in Figures 2(a) and 2(b). One difference is that a PAL Y/C separator also has a PAL modifier that provides a  $90^\circ$  phase shift and removal of the PAL switch inversion. However, the PAL Y/C separator suffers from Hanover bars that result from a real and complementary hue error between pairs of adjacent lines and also cross-color as mentioned above.

As has been demonstrated, the decoding technologies that exist in many of the current NTSC/PAL televisions are unable to keep pace with the ever increasingly dynamic, complex and detailed video sources. Thus, an apparatus and method is needed to provide a cost-effective, flexible and highly scaleable video decoding solution that not only could accommodate the discussed shortcomings of the current NTSC/PAL television decoders, but also could further improve display quality of NTSC/PAL composite signal on other types of display equipment.

09745248 " 122000

**BRIEF DESCRIPTION OF THE DRAWINGS**

The present invention is illustrated by way of example and is not limited by the figures of the accompanying drawings, in which like references indicate similar elements, and in which:

**Figure 1** illustrates a prior art digital decoder for a NTSC/PAL television receiver.

**Figure 2(a)** illustrates one prior art implementation of a Y/C separator.

**Figure 2(b)** illustrates another prior art implementation of a Y/C separator.

**Figure 3** illustrates one embodiment of a general block diagram of an improved video decoder.

**Figure 4** illustrates a block diagram of one general-purpose computer system.

**Figure 5** illustrates a flow chart of one process that one embodiment of improved video decoder follows.

An apparatus and method for decoding a television broadcasting signal are disclosed. In the following description, numerous specific details are set forth in order to provide a thorough understanding of the present invention. However, it will be apparent to one of ordinary skill in the art that the invention may be practiced without these particular details. In other instances, well known elements and theories such as sampling theorem, video processing architecture, video encoding techniques, color space conversion, etc. have not been described in special detail in order to avoid obscuring the present invention.

Both National Television Standards Committee (hereinafter NTSC)/Phase Alternating Line (hereinafter PAL) composite signals are well-known television broadcasting signals and are the sum of a luminance (or brightness) signal and a chrominance (or color) signal. Specifically, the luminance signal, or the Y signal, is derived from gamma-corrected red, green, and blue (or RGB) signals. On the other hand, the chrominance signal, or the C signal, is derived from the differences between the Y signal and the basic red, green, and blue signals. The C signal is further modulated onto a color sub-carrier, where the sub-carrier drives one modulator at sine phase and drives the other modulator at cosine phase. Under the NTSC standard, this color sub-carrier, or a secondary signal that contains additional

Additionally, under the NTSC standard, one video frame consists of two interleaved fields. Each field contains half of the scan lines in the video frame and is displayed in its entirety. Therefore, the odd field is displayed, then the even, then the odd, and so on. Moreover, the scan lines from one field are interlaced with the scan lines in the next field. A “scan line” refers to an individual sweep across the face of the display by the electron beam that makes the video frame. A scan line also comprises a collection of pixels. Throughout this disclosure, “digital signal” and “digitized signal”, are used interchangeably to broadly refer to binary representations of a continuous-time, or an analog, signal. The term, “S-video”, is used for Super-Video, is a technology for transmitting video signals over a cable by dividing the video information into two signals, chrominance and luminance signal. Finally, a machine readable medium refers to, but not limited to, a storage device, a memory device, a carrier wave, etc.

Figure 3 illustrates one embodiment of a general block diagram of the present invention, an improved video decoder (hereinafter IVD). For illustration purposes, the following discussions will mainly focus on the NTSC standard in describing IVD 300. However, it should be apparent to one with ordinary skill in the art to modify

ur

ur

ur

Based on digitized video signal 314, constancy detector 304 then proceeds to calculate a constancy value in a number of dimensions, namely, the horizontal, vertical and temporal dimensions. The constancy value in the horizontal dimension (hereinafter H constancy value) purports to quantify the amount of variation among the discrete samples of digitized video signal 314 on a same scan line. The constancy value in the vertical dimension (hereinafter V constancy value) focuses on



5

1

]

7

Similar to the previously discussed signal adjuster 108 in the Background section, signal adjuster 308 operates further on filtered signal 318 to generate adjusted signal 320. However, unlike signal adjuster 108, signal adjuster 308 does not perform color space conversion in this embodiment. Instead, display encoder 310 encompasses that functionality. Thus, depending on the type of input format display apparatus 324 requires, such as S-video, composite video, etc., display encoder 310 ensures that encoded signal 322 is represented in the appropriate color space and also conforms to the required input format.

A general-purpose computer system 400 is illustrated in Figure 4. The general-purpose computer system architecture comprises microprocessor 402 and cache memory 406 coupled to each other through processor bus 404. Sample computer system 400 also includes high performance system bus 408 and standard I/O bus 428. Coupled to high performance system bus 408 are microprocessor 402 and system controller 410. Additionally, system controller 410 is coupled to

Coupled to graphics controller is video display 418. Coupled to standard I/O bus 428 are I/O controller hub 426, mass storage 430 and alphanumeric input device or other conventional input/output device 432.

Moreover, it should have been apparent to one ordinarily skilled in the art that computer system 400 could be designed with multiple microprocessors 402 and may have more components than that which is shown. Also, mass storage 420 may be used to provide permanent storage for the executable instructions of IVD 300 in one embodiment, whereas memory subsystem 416 may be used to temporarily store the executable instructions and samples of digitized video signal 314 during execution by microprocessor 402. Alternatively, samples of digitized video signal 314 may be stored in dedicated memory 434 (dotted block shown in Figure 4), which is coupled to graphics controller 420.

Figure 5 illustrates a flow chart of one process that one embodiment of IVD 300 follows. In this embodiment, parts of IVD 300 are represented by a set of

In conjunction with Figure 3 and Figure 4, this embodiment of IVD 300 samples NTSC composite signal 312 at 4 times the color sub-carrier frequency in block 500. More specifically, this IVD 300's A/D converter 302 encompasses the functionality of one type of input/output device 432 of general-purpose computer system 400, which receives and converts the analog NTSC composite signal 312 into digitized signal 314. One embodiment of A/D converter 302 also includes some of the mentioned executable instructions of IVD 300. Particularly, in block 502, these executable instructions cause general-purpose computer system 400 to store an appropriate number of samples from digitized signal 314 in either memory subsystem 416 or dedicated memory 434 for further processing.

It is worth noting that NTSC composite signal 312 signal corresponds to a combination of a Y signal and a C signal, which is approximately modulated onto a 3.58 MHz color sub-carrier. Because of the modulation of the C signal, sampling NTSC composite signal 312 at  $(4 * 3.58)$  MHz results in the first sample of digitized signal 314 being 180° out-of-phase with the third sample but in-phase with the fifth

sample. The mathematical relationships between some samples of digitized signal 314 are illustrated with the following equations:

Equation 1  $C = U \sin(wt) + V \cos(wt)$ , where  $w = 2 * \pi * \text{sub-carrier frequency}$

Equation 2  $U * \sin(wt + \pi) = - U * \sin(wt)$

Equation 3  $V * \cos(wt + \pi) = - V * \cos(wt)$

Equation 4 Digitized video signal 314 =  $Y + C$

Equation 5  $S_1 = Y_1 + C_1$

Equation 6  $S_2 = Y_2 + C_2$

Equation 7 If  $S_1$  and  $S_2$  are  $180^\circ$  or  $\pi$  out-of-phase, according to Equations 2 and 3,

$$\begin{aligned} S_1 + S_2 &= (Y_1 + U_1 \sin(wt) + V_1 \cos(wt)) + (Y_2 + U_2 \sin(wt+\pi) + V_2 \cos(wt+\pi)) \\ &= (Y_1 + Y_2) + (U_1 - U_2) \sin(wt) + (V_1 - V_2) \cos(wt) \end{aligned}$$

Equation 8 If  $S_1$  and  $S_2$  are in-phase, then

$$\begin{aligned} S_1 - S_2 &= (Y_1 + U_1 \sin(wt) + V_1 \cos(wt)) - (Y_2 + U_2 \sin(wt) + V_2 \cos(wt)) \\ &= (Y_1 - Y_2) + (U_1 - U_2) \sin(wt) + (V_1 - V_2) \cos(wt) \end{aligned}$$

One embodiment of constancy detector 304 as shown in Figure 3 utilizes the mathematical relationships presented above in calculating the H constancy value.

More particularly, the equation is shown below:

Equation 9 H constancy value =  $\text{abs}(S_1 - S_2)$ , where “abs” stands for “absolute value” and  $S_1$  and  $S_2$  are in-phase.

If samples on one scan line (or horizontal samples) do not vary much relative to one another, as equation 9 above indicates, the H constancy value of the samples would yield a low value. If the H constancy value is less than a predetermined threshold value in block 504, constancy detector 304 then informs Y/C separation engine 306 to proceed with a horizontal filter to distill the luminance and the chrominance information from digitized video signal 314 in block 506. In one implementation, constancy detector 304 assumes a low H constancy value for the samples that fall between the two in-phase samples if the in-phase samples have a low H constancy value.

As an illustration, assuming that the first sample  $S_1$  and its in-phase counterpart, the fifth sample or  $S_2$ , do not vary at all, thus  $Y_1 = Y_2$ ,  $C_1 = C_2$  and the H constancy value = 0. As has been mentioned above, constancy detector 304 assumes that the in-between sample, or third sample ( $S_3$ ), remains constant relative to  $S_1$ . In other words,  $Y_1 = Y_3$  and  $C_1 = C_3$ . Because the H constancy value is less than a non-zero threshold value in block 504, constancy detector 304 informs Y/C separation engine 306 to use a horizontal filter in block 506. Moreover, since  $S_3$  is  $S_1$ 's out-of-phase counterpart, or  $180^\circ$  out-of-phase, the mathematical relationship in equation 7 governs the operations of the horizontal filter. Specifically, one embodiment of the horizontal filter sums  $S_1$  and  $S_3$  to cancel the chrominance information and to yield 2

\*  $Y_1$  (or  $2 * Y_3$ ). Because digitized video signal 314 =  $Y + C$ , this horizontal filter can retrieve the chrominance information by subtracting the luminance information, which results from the application of equation 7, from digitized video signal 314.

However, when horizontal samples change rather abruptly, or the H constancy value exceeds the predetermined threshold in block 504, one embodiment of constancy detector 304 proceeds to determine whether the V constancy value is below a predetermined threshold in block 508. More specifically, constancy detector 304 attempts to detect the amount of changes in a video frame in the vertical direction. Under the NTSC standard, it is important to note that the chrominance signal's phase is shifted by  $180^\circ$  after each scan line in one field. As an illustration, assuming the following:

- $S_1$  represents the first sample of the first scan line
- $S_2$  represents the first sample of the second scan line
- $S_3$  represents the first sample of the third scan line

Equation 10  $S_1 = Y_1 + C_1$

Equation 11  $S_2 = Y_2 - C_2$

Equation 12  $S_3 = Y_3 + C_3$

- $S_1$  represents the first sample in the first field of the first frame (first in time)



- $S_2$  represents the first sample of the first field of the second frame (second in time)
- $S_3$  represents the first sample of the first field of the third frame (third in time)

Equation 16  $S_1 = Y_1 + C_1$

Equation 17  $S_2 = Y_2 - C_2$

Equation 18  $S_3 = Y_3 + C_3$

Again, in order to cancel chrominance information and obtain luminance information, one embodiment of 3-D filter adds up  $S_1$  and  $S_2$ .

Although specific details of one embodiment of constancy detector 304 and Y/C separation engine 306 have been described, it should be apparent to one with ordinary skill in the art to have significantly different designs or implementations and yet still remain within the scope of the present invention. For instance, even though portions of Figure 5 illustrate one sequence that one embodiment of constancy detector 304 follows, constancy detector 304 is not limited to such sequence. For example, constancy detector 304 could start with calculating the T constancy value instead of the H constancy value. Alternatively, constancy detector 304 could compute all three constancy values in parallel.

After Y/C engine 306 separates the chrominance information and the luminance information, signal adjuster 308 as shown in Figure 3 further processes

Display encoder 310 nevertheless needs to make certain that the pixel data from IVD 300 are in recognizable formats (such as 24-bit RGB, 16-bit 4:2:2YcbCr, etc.) to display apparatus 324. On the other hand, if display apparatus 324 requires RGB inputs, display encoder 310 first converts adjusted signal 320, which is in Y/C color space, into RGB color space and then encodes the converted signal into a RGB pixel format that meets the input requirements of display apparatus 324.

Thus, an apparatus and method for decoding a television broadcasting signal have been described. Although an improved video decoder has been described

**000000T 0615Z APR 79**